



# MX-120M

## 19" MIXING AMPLIFIER

Compact and universally deployable mixing amplifier that pumps out 120 Watts. The MX-120M has integrated FM with Bluetooth and a treble/bass tone control on board. It has individual input gain control (3 channels) and is protected against short-circuit and thermal overload.



The MX-120T is a highly versatile amplifier. For use in a shoe shop, but also a local sports hall, council chamber or school – they are all within its scope.

output capacity 100V	120 W
output capacity RMS 8Ω	120 W
frequency range	80 Hz - 16 kHz (+1 dB, -3 dB)
zones	1
direct output	70V / 100V / 4-16 Ω
tone control	bass, treble
built-in music source	USB/SD - FM tuner - Bluetooth
line out	1x RCA (1000 mV / 470 Ω)
MIC input	1x jack 6,3mm (MIC1) 4x euro terminal (MIC1-4 line/mic/ phantom switch)
AUX input	2 RCA
priority levels	1x EMC (euro terminal) EMC>MIC1>MIC2>MIC3>MIC4/AUX1/ AUX2/MP3
power supply	240 V AC
power consumption	180 W
dimintions (h x w x d)	44 x 484 x 260mm - 1RS
weight	3,7kg
extra	remote control
accessories	microphone MIC-621A

