



MX-2406M

6-ZONE 19" SELECTIVE MIXING AMPLIFIER

This versatile mixing amplifier with integrated music source offers 240W output power. You can instantly create six zones operating independently (a single source simultaneously). They each have their own volume level and selective PA option.



The music in the refrigeration aisles is louder than in the checkout area of this supermarket. What's more, you can put out calls for staff per zone.

| | |
|------------------------|--|
| output capacity 100V | 240 W |
| output capacity RMS 8Ω | 240 W |
| frequency range | 50 Hz - 16 kHz |
| zones | 6 |
| direct output | 4-16 Ω / 70V / 100V |
| tone control | yes (per input) |
| built-in music source | USB/SD - FM tuner - Bluetooth |
| line out | yes |
| MIC input | 4 (combo XLR/Jack) + 2 (selective paging RJ45) |
| AUX input | 2 (RCA) |
| chime function | yes |
| priority levels | 5 |
| | EMC input (externally injected signal) |
| | ALARM trigger (built-in) |
| | TEL input / REMOTE MIC (MIC216) |
| | CHIME |
| | MIC1 (prior to MIC2-4/LINE1-2) |
| power supply | 240V AC / 24V DC |
| power consumption | 360W |
| dimensions (h x w x d) | 88 x 484 x 353mm - 2RS |
| weight | 7,2kg |
| accessories | MIC216 / MIC511C / MIC621A |

