



MX-120T

- 100V table-top model/19" mixing amplifier with integrated AM/FM tuner.
- 2 MIC inputs (XLR/phoenix).
- 1 line-in (RCA).
- Short-circuit and thermal protection.
- Including remote control for tuner.

SPECIFICATIONS

output power	120 W
output power RMS 8 Ω	120 W
frequency range	50 Hz - 15 kHz
zones	1
direct output	70 V / 100 V / 4 - 16 Ω
LED level indicator	yes
tone control	yes
built-in source	AM/FM tuner - 100 presets
REC output	no
amp in	yes
pre amp output	yes
MIC input	2
AUX input	1
tape input	0
chime	yes
phantom power supply	no
priority levels	1 MIC (VOX)
power supply	240 V AC
power consumption	200 W
dimensions mm (h x w x d)	88 x 484 x 300
weight	15 kg
extra	remote control FM/AM antenna

OPTIONAL ACCESSORIES

microphones	MIC-621A (power adapter)
-------------	--------------------------

